




# **WEEKLY PROGRAMMABLE TIMER**



## **■ CONNECTION DIAGRAM**



Timer

# DIMENSIONS

I POWER



## DIN Rail Installation

Advanced pre-setting one week before

Digital electronic time switch with daily programs

Repeat programs with 28 on/off setting; and manual over-ride

Lithium battery power reserve

Auto time error correction  $\pm 60$ sec, weekly

## ■ TECHNICAL DATA

Voltage rating: AC 220V 50/60Hz Voltage limit:AC 180V~250V

Hysteresis: ≤1 sec/day (25°C) ON/OFF operation: 28ON & 28OFF

Power consumption: 2VA(max)

Display: LCD

Service life: Mechanial 107

Electrically 105

Minimum interval: 1 minute

Weight: approx 65g

### Order voltage

6V,12V,24V,36V,48V,110V;

Minimum time: 1minutes Longest time: 168 Hours

Load capacity: resistive load:16A/250V AC

Lagging load:10A/250Vac

lamp load:2000W


Switching contact: 1 changeover switch Power reserve: 3 years (Lithium battery) Ambient temperature: -10~+40℃

Ambient humidity:35~85%RH

DI	S	Р	L	Α	Y



## MEANING.



	D+	DAT	
3	H+	HOUR	
4	M+	MIN	
5	<b>(</b>	CLOCK	
6	С	RESET	
7	MANUAL	MANUAL C/R	
8	C/R	Cancel / recovery	

**Digital Time Switch** 

TIMER

# -B WEEKLY PROGRAMMABLE ELECTRONIC TIMER AC220-240V $\epsilon$ 16A(8)A,250AC NO LNC

## Operating Instrustion:

TYPE

Load

- 1. To start switch: press reset Key, At the first time, if you want to the present time, please press "On board, then press D+, H+, M+ to adjust the number to the present time.
- 2. Enter into programming as belows:

Step	Key	Programming
1	Press P	Setting1 ON time(display 1on)
2	Press H+/M+	Setting hours and minutes
3	Press D+	To select same every day,or different time each day
4	Press P	Setting 1 off time (display 1 off)
5	Press H+/M+	Setting hours and minutes turn off time
6	Press D+	If you want the same every day, you need not press this key
7	Repeat step2-6	Set 2-17 on/off time
8	Press <sup>®</sup>	End

If you do not require 17 settings, press " (1)" to the end.

# NOTE:

- 1. Time setting should according to the time sequence, couldn't be set crossly
- 2. System with quit automatically if there's no operating within 10 seconds and no data is saved.
- 3. Function 3,4,5 can not be used simultaneously.